ES1A THRU ES1J

SURFACE MOUNT SUPER FAST RECOVERY RECTIFIER

Reverse Voltage - 50 to 600 Volts Forward Current - 1.0 Ampere

FEATURES

◆Plastic package has underwrites laboratory flammability Classification 94V-0

♦Glass passivated chip junction

◆Built-in strain relief

◆Super Fast switiching speed for high efficiency

♦ High temperature soldering guaranteed 250°C/10 seconds

Mechanical Data

◆Case: Transfer molded plastic


◆Terminals: Solder plated, solderable per

♦ MIL-STD-750, Method 2026

◆Polarity: Color band denotes cathode end

◆ Weight: 0.002ounce, 0.064 gram

SMAF



Dimensions in inches and (millimeters)

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Rating at 25°C ambient temperature unless otherwise specified.

Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%

PARAMETER		SYMBOL	ES1A	ES1B	ES1C	ES1D	ES1E	ES1G	ES1J	UNIT
Maximum Repetitive Peak Reverse Voltage		V _{RRM}	50	100	150	200	300	400	600	VOLTS
Maximum RMS Voltage		V _{RMS}	35	70	105	140	210	280	420	VOLTS
Maximum DC Blocking Voltage		V _{DC}	50	100	150	200	300	400	600	VOLTS
Maximum Average Forward Rectified Current At T_A =55 $^{\circ}$ C		I _(AV)	1.0							Amps
Peak Forward Surge Current 8.3ms single half sine-wave superimposed on rated load (JEDEC Method)		Ігѕм	30						Amps	
Maximum instantaneous forward voltage per at 1.0A		V_{F}	0.95			1.25		1.7	VOLTS	
Maximum DC Reverse Current at Rated DC blocking voltage at	T _A =25℃		5.0 100							- uA
	T _A =125℃	I R								
Maximum Reverse Recovery Time Test conditions I_F =0.5A, I_R =1.0A, I_{RR} =0.25A		t _{rr}	35						nS	
Typical Junction Capacitance (Measured at 1.0MHz and applied reverse voltage of 4.0V)		CJ	10			8		pF		
Typical Thermal Resistance (Note 1)		RөJA	88							°CM
		Røjl	28							
Operating Junction Temperature		T _J	-55 to +150							$^{\circ}\!\mathbb{C}$
Storage Temperature Rang		Тѕтс	-55 to +150							$^{\circ}\!\mathbb{C}$


Note: 1. Thermal resistance from Junction to ambient and from junction to lead mounted on P.C.B. with $0.2 \times 0.2''$ (5.0 × 5.0mm) copper pad areas.


ES1A THRU ES1J


SURFACE MOUNT SUPER FAST RECOVERYRECTIFIER

Reverse Voltage - 50 to 600 Volts Forward Current - 1.0 Ampere


RATING AND CHARACTERISTIC CURVES ES1A THRU ES1J









INSTANTANEOUS FORWARD VOLTAGE.(V)









Note: Specifications are subject to change without notice. For more detail and update, please visit our website.